



ECHATRONIC COMPANY

TRANSFORMATOREN DROSSELN NETZGERÄTE

## Absicherungstabelle Einphasentrafos, Industrie

Typ	Leistung [VA]	Leistungsschalter	550 [V]	525 [V]	500 [V]	480 [V]	460 [V]	440 [V]	415 [V]	400 [V]	380 [V]	240 [V]	230 [V]	220 [V]	208 [V]	200 [V]	
ETI00.20	200		0,40 A	0,42 A	0,44 A	0,46 A	0,48 A	0,50 A	0,53 A	0,55 A	0,58 A	0,92 A	0,96 A	1,00 A	1,06 A	1,10 A	
		3RV1421-0FA10	x	x	x	x	x	x									
		3RV1421-0GA10				x	x	x	x	x	x						
		3RV1421-0KA10											x	x	x	x	x
ETI00.25	250		0,50 A	0,52 A	0,55 A	0,57 A	0,60 A	0,63 A	0,66 A	0,69 A	0,72 A	1,15 A	1,20 A	1,25 A	1,32 A	1,38 A	
		3RV1421-0GA10	x	x	x	x	x	x									
		3RV1421-0HA10				x	x	x	x	x	x						
		3RV1421-1AA10											x	x	x	x	x
ETI00.32	320		0,64 A	0,67 A	0,70 A	0,73 A	0,77 A	0,80 A	0,85 A	0,88 A	0,93 A	1,47 A	1,53 A	1,60 A	1,69 A	1,76 A	
		3RV1421-0HA10	x	x	x	x	x	x									
		3RV1421-0JA10				x	x	x	x	x	x						
		3RV1421-1BA10											x	x	x	x	x
ETI00.40	400		0,80 A	0,84 A	0,88 A	0,92 A	0,96 A	1,00 A	1,06 A	1,10 A	1,16 A	1,83 A	1,91 A	2,00 A	2,12 A	2,20 A	
		3RV1421-0JA10	x	x	x	x	x	x									
		3RV1421-0KA10				x	x	x	x	x	x						
		3RV1421-1CA10											x	x	x	x	x
ETI00.50	500		1,00 A	1,05 A	1,10 A	1,15 A	1,20 A	1,25 A	1,33 A	1,38 A	1,45 A	2,29 A	2,39 A	2,50 A	2,64 A	2,75 A	
		3RV1421-0KA10	x	x	x	x	x	x									
		3RV1421-1AA10				x	x	x	x	x	x						
		3RV1421-1DA10											x	x	x	x	x
ETI00.63	630		1,26 A	1,32 A	1,39 A	1,44 A	1,51 A	1,58 A	1,67 A	1,73 A	1,82 A	2,89 A	3,01 A	3,15 A	3,33 A	3,47 A	
		3RV1421-1AA10	x	x	x	x	x	x									
		3RV1421-1BA10				x	x	x	x	x	x						
		3RV1421-1EA10											x	x	x	x	x
ETI00.80	800		1,60 A	1,68 A	1,76 A	1,83 A	1,91 A	2,00 A	2,12 A	2,20 A	2,32 A	3,67 A	3,83 A	4,00 A	4,23 A	4,40 A	
		3RV1421-1BA10	x	x	x	x	x	x									
		3RV1421-1CA10				x	x	x	x	x	x						
		3RV1421-1FA10											x	x	x	x	x
ETI01.00	1000		2,00 A	2,10 A	2,20 A	2,29 A	2,39 A	2,50 A	2,65 A	2,75 A	2,89 A	4,58 A	4,78 A	5,00 A	5,29 A	5,50 A	
		3RV1421-1CA10	x	x	x	x	x	x									
		3RV1421-1DA10				x	x	x	x	x	x						
		3RV1421-1GA10											x	x	x	x	x
ETI01.30	1300		2,60 A	2,72 A	2,86 A	2,98 A	3,11 A	3,25 A	3,45 A	3,58 A	3,76 A	5,96 A	6,22 A	6,50 A	6,88 A	7,15 A	
		3RV1421-1DA10	x	x	x	x	x	x									
		3RV1421-1EA10				x	x	x	x	x	x						
		3RV1421-1HA10											x	x	x	x	x
ETI01.60	1600		3,20 A	3,35 A	3,52 A	3,67 A	3,83 A	4,00 A	4,24 A	4,40 A	4,63 A	7,33 A	7,65 A	8,00 A	8,46 A	8,80 A	
		3RV1421-1EA10	x	x	x	x	x	x									
		3RV1421-1FA10				x	x	x	x	x	x						
		3RV1421-1JA10											x	x	x	x	x



# ECHATRONIC COMPANY

## TRANSFORMATOREN DROSSELN NETZGERÄTE

Typ	Leistung [VA]	Leistungsschalter	550 [V]	525 [V]	500 [V]	480 [V]	460 [V]	440 [V]	415 [V]	400 [V]	380 [V]	240 [V]	230 [V]	220 [V]	208 [V]	200 [V]	
ETI02.00	2000		4,00 A	4,19 A	4,40 A	4,58 A	4,78 A	5,00 A	5,30 A	5,50 A	5,79 A	9,17 A	9,57 A	10,00 A	10,58 A	11,00 A	
		3RV1421-1FA10	x	x	x	x	x	x									
		3RV1421-1GA10				x	x	x	x	x	x						
		3RV1421-1KA10											x	x	x	x	x
ETI02.50	2500		5,00 A	5,24 A	5,50 A	5,73 A	5,98 A	6,25 A	6,63 A	6,88 A	7,24 A	11,46 A	11,96 A	12,50 A	13,22 A	13,75 A	
		3RV1421-1GA10	x	x	x	x	x	x									
		3RV1421-1HA10								x	x	x					
		3RV1421-4AA10											x	x	x	x	x
ETI03.20	3200		6,40 A	6,70 A	7,04 A	7,33 A	7,65 A	8,00 A	8,48 A	8,80 A	9,26 A	14,67 A	15,30 A	16,00 A	16,92 A	17,60 A	
		3RV1421-1HA10	x	x	x	x	x	x									
		3RV1421-1JA10				x	x	x	x	x	x						
		3RV1421-4BA10											x	x	x	x	x
ETI04.00	4000		8,00 A	8,38 A	8,80 A	9,17 A	9,57 A	10,00 A	10,60 A	11,00 A	11,58 A	18,33 A	19,13 A	20,00 A	21,15 A	22,00 A	
		3RV1421-1JA10	x	x	x	x	x	x									
		3RV1421-4KA10				x	x	x	x	x	x						
		3RV1431-4DA10											x	x	x	x	x
ETI05.00	5000		10,00 A	10,48 A	11,00 A	11,46 A	11,96 A	12,50 A	13,25 A	13,75 A	14,47 A	22,92 A	23,91 A	25,00 A	26,44 A	27,50 A	
		3RV1421-1KA10	x	x	x	x	x	x									
		3RV1421-4AA10				x	x	x	x	x	x						
		3RV1431-4EA10											x	x	x	x	x
ETI06.30	6300		12,60 A	13,20 A	13,86 A	14,44 A	15,07 A	15,75 A	16,70 A	17,33 A	18,24 A	28,88 A	30,13 A	31,50 A	33,32 A	34,65 A	
		3RV1421-4AA10	x	x	x	x	x	x									
		3RV1431-4BA10								x	x	x					
		3RV1431-4FA10											x	x	x	x	x
ETI08.00	8000		16,00 A	16,76 A	17,60 A	18,33 A	19,13 A	20,00 A	21,20 A	22,00 A	23,16 A	36,67 A	38,26 A	40,00 A	42,31 A	44,00 A	
		3RV1431-4BA10	x	x	x	x	x	x									
		3RV1431-4DA10				x	x	x	x	x	x						
		3RV1431-4FA10											x	x	x		
		auf Anfrage															
ETI10.00	10000		20 A	21 A	22 A	23 A	24 A	25 A	27 A	28 A	29 A	46 A	48 A	50 A	53 A	55 A	
		3RV1431-4DA10	x	x	x	x	x	x									
		3RV1431-4EA10				x	x	x	x	x	x						
				auf Anfrage													
ETI13.00	13000		26 A	27 A	29 A	30 A	31 A	33 A	34 A	36 A	38 A	60 A	62 A	65 A	69 A	72 A	
		3RV1431-4EA10	x	x	x	x	x										
		3RV1431-4FA10				x	x	x	x	x	x						
				auf Anfrage													
ETI16.00	16000		32 A	34 A	35 A	37 A	38 A	40 A	42 A	44 A	46 A	73 A	77 A	80 A	85 A	88 A	
		3RV1431-4FA10	x	x	x	x	x	x									
				auf Anfrage													
ETI20.00	20000		40 A	42 A	44 A	46 A	48 A	50 A	53 A	55 A	58 A	92 A	96 A	100 A	106 A	110 A	
		auf Anfrage															
ETI25.00	25000		50 A	52 A	55 A	57 A	60 A	63 A	66 A	69 A	72 A	115 A	120 A	125 A	132 A	138 A	
		auf Anfrage															



# ECHATRONIC COMPANY

## TRANSFORMATOREN DROSSELN NETZGERÄTE

Typ	Leistung [VA]	Leistungsschalter	550 [V]	525 [V]	500 [V]	480 [V]	460 [V]	440 [V]	415 [V]	400 [V]	380 [V]	240 [V]	230 [V]	220 [V]	208 [V]	200 [V]
ETI32.00	32000		64 A	67 A	70 A	73 A	77 A	80 A	85 A	88 A	93 A	147 A	153 A	160 A	169 A	176 A
		auf Anfrage														
ETI40.00	40000		80 A	84 A	88 A	92 A	96 A	100 A	106 A	110 A	116 A	183 A	191 A	200 A	212 A	220 A
		auf Anfrage														
ETI50.00	50000		100 A	105 A	110 A	115 A	120 A	125 A	133 A	138 A	145 A	229 A	239 A	250 A	264 A	275 A
		auf Anfrage														
ETI63.00	63000		126 A	132 A	139 A	144 A	151 A	158 A	167 A	173 A	182 A	289 A	301 A	315 A	333 A	347 A
		auf Anfrage														
ETI80.00	80000		160 A	168 A	176 A	183 A	191 A	200 A	212 A	220 A	232 A	367 A	383 A	400 A	423 A	440 A
		auf Anfrage														
ETI100.00	100000		200 A	210 A	220 A	229 A	239 A	250 A	265 A	275 A	289 A	458 A	478 A	500 A	529 A	550 A
		auf Anfrage														